

Please type a plus sign (+) inside this box → ☐

PTO/SB/05 (4/98)
Approved for use through 09/30/2000. OMB 0651-0032
Patent and Trademark Office: U.S. DEPARTMENT OF COMMERCE
Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it displays a valid OMB control number.

UTILITY PATENT APPLICATION TRANSMITTAL

(Only for new nonprovisional applications under 37 C.F.R. § 1.53(b))

Attorney Docket No. 2000-003
First Inventor or Application Identifier Charles C. Romaniuk
Title Pulse Controlled Phase Modulator
Express Mail Label No.

APPLICATION ELEMENTS

See MPEP chapter 600 concerning utility patent application contents.

1. ☒ * Fee Transmittal Form (e.g., PTO/SB/17)
(Submit an original and a duplicate for fee processing)
2. ☒ Specification [Total Pages 21]
(preferred arrangement set forth below)
 - Descriptive title of the invention
 - Cross References to Related Applications
 - Statement Regarding Fed sponsored R & D
 - Reference to Microfiche Appendix
 - Background of the invention
 - Brief Summary of the invention
 - Brief Description of the Drawings (if filed)
 - Detailed Description
 - Claim(s)
 - Abstract of the Disclosure
3. ☒ Drawing(s) (35 U.S.C. 113) [Total Sheets 8]
4. Oath or Declaration [Total Pages 2]
 - a. ☒ Newly executed (original or copy)
 - b. ☐ Copy from a prior application (37 C.F.R. § 1.63(d))
(for continuation/divisional with Box 16 completed)
 - i. ☐ DELETION OF INVENTOR(S)
Signed statement attached deleting inventor(s) named in the prior application, see 37 C.F.R. §§ 1.63(d)(2) and 1.33(b).

* NOTE FOR ITEMS 1 & 13: IN ORDER TO BE ENTITLED TO PAY SMALL ENTITY FEES, A SMALL ENTITY STATEMENT IS REQUIRED (37 C.F.R. § 1.27), EXCEPT IF ONE FILED IN A PRIOR APPLICATION IS RELIED UPON (37 C.F.R. § 1.28).

ADDRESS TO: Assistant Commissioner for Patents
Box Patent Application
Washington, DC 20231

5. ☐ Microfiche Computer Program (Appendix)
6. Nucleotide and/or Amino Acid Sequence Submission (if applicable, all necessary)
 - a. ☐ Computer Readable Copy
 - b. ☐ Paper Copy (identical to computer copy)
 - c. ☐ Statement verifying identity of above copies

ACCOMPANYING APPLICATION PARTS

7. ☐ Assignment Papers (cover sheet & document(s))
8. ☐ 37 C.F.R. § 3.73(b) Statement of Power of Attorney (when there is an assignee)
9. ☐ English Translation Document (if applicable)
10. ☒ Information Disclosure Statement (IDS)/PTO-1449 ☒ Copies of IDS Citations
11. ☐ Preliminary Amendment
12. ☒ Return Receipt Postcard (MPEP 503)
(Should be specifically itemized)
13. ☐ * Small Entity Statement(s) ☒ Statement filed in prior application, Status still proper and desired (PTO/SB/09-12)
14. ☐ Certified Copy of Priority Document(s) (if foreign priority is claimed)
15. ☐ Other: _____

16. If a CONTINUING APPLICATION, check appropriate box, and supply the requisite information below and in a preliminary amendment:

☐ Continuation ☐ Divisional ☐ Continuation-in-part (CIP) of prior application No: _____
Prior application information: Examiner _____ Group / Art Unit: _____

For CONTINUATION or DIVISIONAL APPS only: The entire disclosure of the prior application, from which an oath or declaration is supplied under Box 4b, is considered a part of the disclosure of the accompanying continuation or divisional application and is hereby incorporated by reference. The incorporation can only be relied upon when a portion has been inadvertently omitted from the submitted application parts.

17. CORRESPONDENCE ADDRESS

☐ Customer Number or Bar Code Label

(Insert Customer No. or Attach bar code label here)

or ☒ Correspondence address below

Name	Charles C. Romaniuk				
	Box 3295				
Address					
City	Vermilion	State	Alberta	Zip Code	T9X 2B2
Country	Canada	Telephone	(403) 861-6944	Fax	

Name (Print/Type)	Charles C. Romaniuk	Registration No. (Attorney/Agent)	
Signature	Charles Romaniuk	Date	09/20/00

Burden Hour Statement: This form is estimated to take 0.2 hours to complete. Time will vary depending upon the needs of the individual case. Any comments on the amount of time you are required to complete this form should be sent to the Chief Information Officer, Patent and Trademark Office, Washington, DC 20231. DO NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. SEND TO: Assistant Commissioner for Patents, Box Patent Application, Washington, DC 20231.

<h1 style="margin: 0;">FEE TRANSMITTAL</h1> <h2 style="margin: 0;">for FY 2000</h2> <p style="font-size: small; margin: 0;">Patent fees are subject to annual revision. Small Entity payments <u>must</u> be supported by a small entity statement, otherwise large entity fees must be paid. See Forms PTO/SB/09-12. See 37 C.F.R. §§ 1.27 and 1.28.</p>		Complete if Known	
TOTAL AMOUNT OF PAYMENT (\$) 462		Application Number	
		Filing Date	
		First Named Inventor Charles C. Romaniuk	
		Examiner Name	
		Group / Art Unit	
		Attorney Docket No. 2000-003	

METHOD OF PAYMENT (check one)	FEE CALCULATION (continued)																																																																																																																																																																																		
<p>1. <input type="checkbox"/> The Commissioner is hereby authorized to charge indicated fees and credit any overpayments to:</p> <p>Deposit Account Number </p> <p>Deposit Account Name </p> <p><input type="checkbox"/> Charge Any Additional Fee Required Under 37 CFR §§ 1.16 and 1.17</p> <p>2. <input checked="" type="checkbox"/> Payment Enclosed:</p> <p><input type="checkbox"/> Check <input checked="" type="checkbox"/> Money Order <input type="checkbox"/> Other</p>	<p>3. ADDITIONAL FEES</p> <table border="1" style="width: 100%; border-collapse: collapse; font-size: x-small;"> <thead> <tr> <th colspan="2">Large Entity</th> <th colspan="2">Small Entity</th> <th rowspan="2">Fee Description</th> <th rowspan="2">Fee Paid</th> </tr> <tr> <th>Fee Code</th> <th>Fee (\$)</th> <th>Fee Code</th> <th>Fee (\$)</th> </tr> </thead> <tbody> <tr><td>105</td><td>130</td><td>205</td><td>65</td><td>Surcharge - late filing fee or oath</td><td></td></tr> <tr><td>127</td><td>50</td><td>227</td><td>25</td><td>Surcharge - late provisional filing fee or cover sheet.</td><td></td></tr> <tr><td>139</td><td>130</td><td>139</td><td>130</td><td>Non-English specification</td><td></td></tr> <tr><td>147</td><td>2,520</td><td>147</td><td>2,520</td><td>For filing a request for reexamination</td><td></td></tr> <tr><td>112</td><td>920*</td><td>112</td><td>920*</td><td>Requesting publication of SIR prior to Examiner action</td><td></td></tr> <tr><td>113</td><td>1,840*</td><td>113</td><td>1,840*</td><td>Requesting publication of SIR after Examiner action</td><td></td></tr> <tr><td>115</td><td>110</td><td>215</td><td>55</td><td>Extension for reply within first month</td><td></td></tr> <tr><td>116</td><td>380</td><td>216</td><td>190</td><td>Extension for reply within second month</td><td></td></tr> <tr><td>117</td><td>870</td><td>217</td><td>435</td><td>Extension for reply within third month</td><td></td></tr> <tr><td>118</td><td>1,360</td><td>218</td><td>680</td><td>Extension for reply within fourth month</td><td></td></tr> <tr><td>128</td><td>1,850</td><td>228</td><td>925</td><td>Extension for reply within fifth month</td><td></td></tr> <tr><td>119</td><td>300</td><td>219</td><td>150</td><td>Notice of Appeal</td><td></td></tr> <tr><td>120</td><td>300</td><td>220</td><td>150</td><td>Filing a brief in support of an appeal</td><td></td></tr> <tr><td>121</td><td>260</td><td>221</td><td>130</td><td>Request for oral hearing</td><td></td></tr> <tr><td>138</td><td>1,510</td><td>138</td><td>1,510</td><td>Petition to institute a public use proceeding</td><td></td></tr> <tr><td>140</td><td>110</td><td>240</td><td>55</td><td>Petition to revive - unavoidable</td><td></td></tr> <tr><td>141</td><td>1,210</td><td>241</td><td>605</td><td>Petition to revive - unintentional</td><td></td></tr> <tr><td>142</td><td>1,210</td><td>242</td><td>605</td><td>Utility issue fee (or reissue)</td><td></td></tr> <tr><td>143</td><td>430</td><td>243</td><td>215</td><td>Design issue fee</td><td></td></tr> <tr><td>144</td><td>580</td><td>244</td><td>290</td><td>Plant issue fee</td><td></td></tr> <tr><td>122</td><td>130</td><td>122</td><td>130</td><td>Petitions to the Commissioner</td><td></td></tr> <tr><td>123</td><td>50</td><td>123</td><td>50</td><td>Petitions related to provisional applications</td><td></td></tr> <tr><td>126</td><td>240</td><td>126</td><td>240</td><td>Submission of Information Disclosure Stmt</td><td></td></tr> <tr><td>581</td><td>40</td><td>581</td><td>40</td><td>Recording each patent assignment per property (times number of properties)</td><td></td></tr> <tr><td>146</td><td>690</td><td>246</td><td>345</td><td>Filing a submission after final rejection (37 CFR § 1.129(a))</td><td></td></tr> <tr><td>149</td><td>690</td><td>249</td><td>345</td><td>For each additional invention to be examined (37 CFR § 1.129(b))</td><td></td></tr> <tr><td colspan="5">Other fee (specify) _____</td><td></td></tr> <tr><td colspan="5">Other fee (specify) _____</td><td></td></tr> </tbody> </table>	Large Entity		Small Entity		Fee Description	Fee Paid	Fee Code	Fee (\$)	Fee Code	Fee (\$)	105	130	205	65	Surcharge - late filing fee or oath		127	50	227	25	Surcharge - late provisional filing fee or cover sheet.		139	130	139	130	Non-English specification		147	2,520	147	2,520	For filing a request for reexamination		112	920*	112	920*	Requesting publication of SIR prior to Examiner action		113	1,840*	113	1,840*	Requesting publication of SIR after Examiner action		115	110	215	55	Extension for reply within first month		116	380	216	190	Extension for reply within second month		117	870	217	435	Extension for reply within third month		118	1,360	218	680	Extension for reply within fourth month		128	1,850	228	925	Extension for reply within fifth month		119	300	219	150	Notice of Appeal		120	300	220	150	Filing a brief in support of an appeal		121	260	221	130	Request for oral hearing		138	1,510	138	1,510	Petition to institute a public use proceeding		140	110	240	55	Petition to revive - unavoidable		141	1,210	241	605	Petition to revive - unintentional		142	1,210	242	605	Utility issue fee (or reissue)		143	430	243	215	Design issue fee		144	580	244	290	Plant issue fee		122	130	122	130	Petitions to the Commissioner		123	50	123	50	Petitions related to provisional applications		126	240	126	240	Submission of Information Disclosure Stmt		581	40	581	40	Recording each patent assignment per property (times number of properties)		146	690	246	345	Filing a submission after final rejection (37 CFR § 1.129(a))		149	690	249	345	For each additional invention to be examined (37 CFR § 1.129(b))		Other fee (specify) _____						Other fee (specify) _____					
Large Entity		Small Entity		Fee Description	Fee Paid																																																																																																																																																																														
Fee Code	Fee (\$)	Fee Code	Fee (\$)																																																																																																																																																																																
105	130	205	65	Surcharge - late filing fee or oath																																																																																																																																																																															
127	50	227	25	Surcharge - late provisional filing fee or cover sheet.																																																																																																																																																																															
139	130	139	130	Non-English specification																																																																																																																																																																															
147	2,520	147	2,520	For filing a request for reexamination																																																																																																																																																																															
112	920*	112	920*	Requesting publication of SIR prior to Examiner action																																																																																																																																																																															
113	1,840*	113	1,840*	Requesting publication of SIR after Examiner action																																																																																																																																																																															
115	110	215	55	Extension for reply within first month																																																																																																																																																																															
116	380	216	190	Extension for reply within second month																																																																																																																																																																															
117	870	217	435	Extension for reply within third month																																																																																																																																																																															
118	1,360	218	680	Extension for reply within fourth month																																																																																																																																																																															
128	1,850	228	925	Extension for reply within fifth month																																																																																																																																																																															
119	300	219	150	Notice of Appeal																																																																																																																																																																															
120	300	220	150	Filing a brief in support of an appeal																																																																																																																																																																															
121	260	221	130	Request for oral hearing																																																																																																																																																																															
138	1,510	138	1,510	Petition to institute a public use proceeding																																																																																																																																																																															
140	110	240	55	Petition to revive - unavoidable																																																																																																																																																																															
141	1,210	241	605	Petition to revive - unintentional																																																																																																																																																																															
142	1,210	242	605	Utility issue fee (or reissue)																																																																																																																																																																															
143	430	243	215	Design issue fee																																																																																																																																																																															
144	580	244	290	Plant issue fee																																																																																																																																																																															
122	130	122	130	Petitions to the Commissioner																																																																																																																																																																															
123	50	123	50	Petitions related to provisional applications																																																																																																																																																																															
126	240	126	240	Submission of Information Disclosure Stmt																																																																																																																																																																															
581	40	581	40	Recording each patent assignment per property (times number of properties)																																																																																																																																																																															
146	690	246	345	Filing a submission after final rejection (37 CFR § 1.129(a))																																																																																																																																																																															
149	690	249	345	For each additional invention to be examined (37 CFR § 1.129(b))																																																																																																																																																																															
Other fee (specify) _____																																																																																																																																																																																			
Other fee (specify) _____																																																																																																																																																																																			
<p style="text-align: center;">FEE CALCULATION</p> <p>1. BASIC FILING FEE</p> <table border="1" style="width: 100%; border-collapse: collapse; font-size: x-small;"> <thead> <tr> <th colspan="2">Large Entity</th> <th colspan="2">Small Entity</th> <th rowspan="2">Fee Description</th> <th rowspan="2">Fee Paid</th> </tr> <tr> <th>Fee Code</th> <th>Fee (\$)</th> <th>Fee Code</th> <th>Fee (\$)</th> </tr> </thead> <tbody> <tr><td>101</td><td>690</td><td>201</td><td>345</td><td>Utility filing fee</td><td>345</td></tr> <tr><td>106</td><td>310</td><td>206</td><td>155</td><td>Design filing fee</td><td></td></tr> <tr><td>107</td><td>480</td><td>207</td><td>240</td><td>Plant filing fee</td><td></td></tr> <tr><td>108</td><td>690</td><td>208</td><td>345</td><td>Reissue filing fee</td><td></td></tr> <tr><td>114</td><td>150</td><td>214</td><td>75</td><td>Provisional filing fee</td><td></td></tr> <tr><td colspan="5">SUBTOTAL (1)</td><td>(\$) 345</td></tr> </tbody> </table> <p>2. EXTRA CLAIM FEES</p> <table border="1" style="width: 100%; border-collapse: collapse; font-size: x-small;"> <thead> <tr> <th colspan="2">Total Claims</th> <th colspan="2">Extra Claims</th> <th colspan="2">Fee from below</th> <th colspan="2">Fee Paid</th> </tr> </thead> <tbody> <tr> <td>33</td> <td>-20** = 13</td> <td>13</td> <td>X</td> <td>9</td> <td>=</td> <td>117</td> <td></td> </tr> <tr> <td>1</td> <td>-3** = 0</td> <td>0</td> <td>X</td> <td></td> <td>=</td> <td>0</td> <td></td> </tr> <tr> <td colspan="8">Multiple Dependent</td> </tr> </tbody> </table> <p><small>**or number previously paid, if greater; For Reissues, see below</small></p> <table border="1" style="width: 100%; border-collapse: collapse; font-size: x-small;"> <thead> <tr> <th colspan="2">Large Entity</th> <th colspan="2">Small Entity</th> <th rowspan="2">Fee Description</th> <th rowspan="2">Fee Paid</th> </tr> <tr> <th>Fee Code</th> <th>Fee (\$)</th> <th>Fee Code</th> <th>Fee (\$)</th> </tr> </thead> <tbody> <tr><td>103</td><td>18</td><td>203</td><td>9</td><td>Claims in excess of 20</td><td></td></tr> <tr><td>102</td><td>78</td><td>202</td><td>39</td><td>Independent claims in excess of 3</td><td></td></tr> <tr><td>104</td><td>260</td><td>204</td><td>130</td><td>Multiple dependent claim, if not paid</td><td></td></tr> <tr><td>109</td><td>78</td><td>209</td><td>39</td><td>** Reissue independent claims over original patent</td><td></td></tr> <tr><td>110</td><td>18</td><td>210</td><td>9</td><td>** Reissue claims in excess of 20 and over original patent</td><td></td></tr> <tr><td colspan="5">SUBTOTAL (2)</td><td>(\$) 117</td></tr> </tbody> </table>	Large Entity		Small Entity		Fee Description	Fee Paid	Fee Code	Fee (\$)	Fee Code	Fee (\$)	101	690	201	345	Utility filing fee	345	106	310	206	155	Design filing fee		107	480	207	240	Plant filing fee		108	690	208	345	Reissue filing fee		114	150	214	75	Provisional filing fee		SUBTOTAL (1)					(\$) 345	Total Claims		Extra Claims		Fee from below		Fee Paid		33	-20** = 13	13	X	9	=	117		1	-3** = 0	0	X		=	0		Multiple Dependent								Large Entity		Small Entity		Fee Description	Fee Paid	Fee Code	Fee (\$)	Fee Code	Fee (\$)	103	18	203	9	Claims in excess of 20		102	78	202	39	Independent claims in excess of 3		104	260	204	130	Multiple dependent claim, if not paid		109	78	209	39	** Reissue independent claims over original patent		110	18	210	9	** Reissue claims in excess of 20 and over original patent		SUBTOTAL (2)					(\$) 117	<p>SUBTOTAL (3) (\$) 0</p> <p><small>*Reduced by Basic Filing Fee Paid</small></p>																																																						
Large Entity		Small Entity		Fee Description			Fee Paid																																																																																																																																																																												
Fee Code	Fee (\$)	Fee Code	Fee (\$)																																																																																																																																																																																
101	690	201	345	Utility filing fee	345																																																																																																																																																																														
106	310	206	155	Design filing fee																																																																																																																																																																															
107	480	207	240	Plant filing fee																																																																																																																																																																															
108	690	208	345	Reissue filing fee																																																																																																																																																																															
114	150	214	75	Provisional filing fee																																																																																																																																																																															
SUBTOTAL (1)					(\$) 345																																																																																																																																																																														
Total Claims		Extra Claims		Fee from below		Fee Paid																																																																																																																																																																													
33	-20** = 13	13	X	9	=	117																																																																																																																																																																													
1	-3** = 0	0	X		=	0																																																																																																																																																																													
Multiple Dependent																																																																																																																																																																																			
Large Entity		Small Entity		Fee Description	Fee Paid																																																																																																																																																																														
Fee Code	Fee (\$)	Fee Code	Fee (\$)																																																																																																																																																																																
103	18	203	9	Claims in excess of 20																																																																																																																																																																															
102	78	202	39	Independent claims in excess of 3																																																																																																																																																																															
104	260	204	130	Multiple dependent claim, if not paid																																																																																																																																																																															
109	78	209	39	** Reissue independent claims over original patent																																																																																																																																																																															
110	18	210	9	** Reissue claims in excess of 20 and over original patent																																																																																																																																																																															
SUBTOTAL (2)					(\$) 117																																																																																																																																																																														

SUBMITTED BY		Complete (if applicable)	
Name (Print/Type)	Charles C. Romaniuk	Registration No. (Attorney/Agent)	Telephone (403) 861-6944
Signature	<i>Charles Romaniuk</i>	Date	09/20/00

WARNING:

Information on this form may become public. Credit card information should not be included on this form. Provide credit card information and authorization on PTO-2038.

Burden Hour Statement: This form is estimated to take 0.2 hours to complete. Time will vary depending upon the needs of the individual case. Any comments on the amount of time you are required to complete this form should be sent to the Chief Information Officer, Patent and Trademark Office, Washington, DC 20231. DO NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. SEND TO: Assistant Commissioner for Patents, Washington, DC 20231.

Reply postcard (MPEP 503/R-1)

Name: Charles Christopher Romaniuk

Title of invention: Pulse Controlled Phase Modulator

Docket No. 2000-003

Date of filing: _____

Serial number of application: _____

Fee Payment: U.S. Money order for \$462

1 page Reply Postcard (MPEP 503/R-1)
and self-addressed stamped envelope

1 page Inventor Information
2 pages Declaration for Utility or Design Patent Application (PTO/SB/01)
1 page Utility Patent Application Transmittal (PTO/SB/05)
2 pages Information Disclosure Statement By Applicant (PTO/SB/08A and 08B)
1 page Statement Claiming Small Entity Status – Independent Inventor (PTO/SB/09)
1 page Fee Transmittal for FY 2000 (PTO/SB/17) (original)
1 page Fee Transmittal for FY 2000 (PTO/SB/17) (duplicate)

16 pages Description
4 pages Claims – 33 claims
1 page Abstract of the Disclosure

21 pages Application

8 sheets Final Drawings

7 pages Citation AA (U.S. Patent # 4,817,207)
12 pages Citation AB (U.S. Patent # 5,274,651)
7 pages Citation AC (U.S. Patent # 6,035,079)
12 pages Citation AD (Bopp, M., Hüther, G., Spatscheck, Th., Specker, H., &
Wiesmann, Th. (1991).)
12 pages Citation AE (Merchele, G.S. (1992).)
10 pages Citation AF (Merchele, G.S. & Henderson, R.J. (1991).)
3 pages Citation AG (Stremmler, F.G. (1990).)

63 pages Information Disclosure Citations (AA to AG)

**STATEMENT CLAIMING SMALL ENTITY STATUS
(37 CFR 1.9(f) & 1.27(b))--INDEPENDENT INVENTOR**

Docket Number (Optional)

2000-003

Applicant, Patentee, or Identifier: Charles C. Romaniuk

Application or Patent No.: _____

Filed or Issued: _____

Title: Pulse Controlled Phase Modulator

As a below named inventor, I hereby state that I qualify as an independent inventor as defined in 37 CFR 1.9(c) for purposes of paying reduced fees to the Patent and Trademark Office described in:

- ☒ the specification filed herewith with title as listed above.
☐ the application identified above.
☐ the patent identified above.

I have not assigned, granted, conveyed, or licensed, and am under no obligation under contract or law to assign, grant, convey, or license, any rights in the invention to any person who would not qualify as an independent inventor under 37 CFR 1.9(c) if that person had made the invention, or to any concern which would not qualify as a small business concern under 37 CFR 1.9(d) or a nonprofit organization under 37 CFR 1.9(e).

Each person, concern, or organization to which I have assigned, granted, conveyed, or licensed or am under an obligation under contract or law to assign, grant, convey, or license any rights in the invention is listed below:

- ☒ No such person, concern, or organization exists.
☐ Each such person, concern, or organization is listed below.

Separate statements are required from each named person, concern, or organization having rights to the invention stating their status as small entities. (37 CFR 1.27)

I acknowledge the duty to file, in this application or patent, notification of any change in status resulting in loss of entitlement to small entity status prior to paying, or at the time of paying, the earliest of the issue fee or any maintenance fee due after the date on which status as a small entity is no longer appropriate. (37 CFR 1.28(b))

Charles C. Romaniuk
NAME OF INVENTOR

NAME OF INVENTOR

NAME OF INVENTOR

Charles C. Romaniuk
Signature of inventor

Signature of inventor

Signature of inventor

09/20/00
Date

Date

Date

INVENTOR INFORMATION

Inventor One Given Name:: Charles C
Family Name:: Romaniuk
Postal Address Line One:: Box 3295
City:: Vermilion
State or Province:: Alberta
Country:: Canada
Postal or Zip Code:: T9X 2B2
City of Residence:: Calgary
State or Province of Residence:: Alberta
Country of Residence:: Canada
Citizenship Country:: Canada

CORRESPONDENCE INFORMATION

Name Line One:: Charles Christopher Romaniuk
Address Line One:: Box 3295
City:: Vermilion
State or Province:: Alberta
Country:: Canada
Postal or Zip Code:: T9X 2B2
Telephone One:: (403) 861-6944
Electronic Mail One:: romaniuks@softhome.net

APPLICATION INFORMATION

Title Line One:: PULSE CONTROLLED PHASE MODULATOR
Total Drawing Sheets:: 8
Formal Drawings?: Yes
Application Type:: Utility
Docket Number:: 2000-003
Secrecy Order in Parent Appl.?: No

Source:: PrintEFS Version 1.0.1

PULSE CONTROLLED PHASE MODULATOR

CROSS-REFERENCE TO RELATED APPLICATIONS

5 Not Applicable

STATEMENT REGARDING FEDERALLY SPONSORED RESEARCH OR DEVELOPMENT

Not Applicable

10

Reference to a "Microfiche appendix"

Not Applicable

BACKGROUND OF THE INVENTION

15 1. Field of the Invention

The present invention relates generally to optical phase modulators and relates specifically to optical phase modulators controlled by a pulsed optical input signal.

2. Discussion of Related Art

20 Optical phase modulators are commonly used devices and are well known in the art. They are useful for converting an electrical, acoustical, or optical signal to an optical signal with a specific phase value. Optical phase modulators have also been developed as optical devices for logic gates and signal receivers. A variety of optical phase modulators are used to provide digital binary phase shift keying (BPSK) modulated signals. However, a more efficient and faster phase modulator
25 which can receive a pulsed input signal of unknown phase, such as a transmission line signal, is needed.

Electro-optic phase modulators are commonly used to phase modulate optical signals using electronic signals. An electronic signal is used to produce an optical effect, such as the Pockels effect or the Kerr effect, thereby modulating the refractive index, and thus the phase delay, of an
30 optical material. These devices are relatively slow and usually require a large electronic signal to produce a large phase shift. As well, using this method a pulsed optical signal must be converted to an electronic signal before it can be used to phase modulate another optical signal. These devices

are not well suited for phase modulating one optical signal with another pulsed optical signal, and are not as efficient as an optical pulse controlled phase modulator.

U.S. patent #5,274,651 describes a method of self-phase modulation that uses a pulsed input signal. The pulsed input signal creates a self-induced intensity-dependent refractive index change and phase modulates itself based on the intensity of the pulsed input signal. A second optical signal can also be used to modulate the refractive index of a first signal according to the intensity of both signals. However, this method does not phase modulate the input signal relative to a known phase value and, therefore, the phase of the signal is still not known after modulation.

In an alternative method, a second optical signal is used to modulate the refractive index of a first signal that has a known phase. However, the optical refractive index change is a relatively weak physical effect, usually requiring large modulating signals and materials with large nonlinear properties.

Some optical phase modulators based on signal interference are used as all-optical logic devices for optically controlled phase modulation. However, these devices are limited to signals with known relative phase values. Pulsed input signals with unknown phase values cannot be properly processed and utilized by these devices because the pulsed input signals, of unknown phase, will not interfere with the device signals, of known phase, as desired.

Other means are also used also for receiving pulsed signals with unknown phase values and converting them to other signals. A heterodyne receiver uses beat interference with a local oscillator to detect a received signal and convert the beat interference to an electronic signal. A homodyne receiver tries to determine the phase of the received signal by combining the received signal with several signals from a local oscillator having various phase values. However, heterodyne and homodyne receivers require some electronic control and are more complex, less efficient, and slower than a pulse controlled phase modulator.

A simpler, more efficient, and dedicated optical phase modulator that can convert a pulsed input signal with unknown phase to a digital BPSK signal is needed.

BRIEF SUMMARY OF THE INVENTION

The pulse controlled phase modulator is a simple device consisting of a splitter, an independent stage, a dependent stage, and a combiner. The splitter receives the continuous wave input signal and divides it into two signals: an independent signal and a dependent signal. Connected to the splitter are the independent stage and the dependent stage. The independent stage produces a processed independent signal and the dependent stage produces a processed dependent

signal. The processed independent signal is maintained as a comparison to the processed dependent signal and is used to produce a continuous wave phase modulated output signal. The dependent stage is used to convert the switching mechanism from an unknown phase pulsed input signal to a pulsed processed dependent signal with a known phase that is opposite in phase to and twice the magnitude of the processed independent signal. The processed dependent signal and the processed independent signal are then directed into the combiner which combines them to generate the constant magnitude continuous wave output signal. The magnitude of the processed dependent signal and the magnitude of the processed independent signal are preferably proportioned so that the combiner combines them to produce two possible output signals of equal magnitude and opposite phase.

The pulse controlled phase modulator produces a phase modulated output signal from a pulsed input signal more efficiently than previous methods by using a switch, such as a threshold device, preferably operating near its threshold, in the dependent stage, to pulse modulate the dependent signal with the pulsed input signal. The resulting dependent signal that is pulsed is combined with the independent signal to produce the continuous wave output signal.

The pulse controlled phase modulator receives a continuous wave coherent input signal and a pulsed input signal with unknown phase and produces a continuous wave phase modulated output signal. The output signal is a substantially constant magnitude binary phase shift keying (BPSK) signal with the same frequency as the continuous wave input signal.

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWINGS

FIG. 1 is a plan view of a pulse controlled phase modulator;

FIG. 2 shows example input and output waveforms of the device of FIG. 1;

FIG. 3 shows a schematic of a pulse controlled phase modulator of FIG. 1;

FIG. 4 is an alternative embodiment of FIG. 1;

FIG. 5 is a further alternative embodiment of FIG. 1;

FIG. 6 is another alternative embodiment of FIG. 1;

FIG. 7 is another alternative embodiment of FIG. 1;

FIG. 8 is a schematic of a circuit using a pulse controlled phase modulator of FIG. 1 as an external signal receiver; and

FIG. 9 is a design example of FIG. 3.

DETAILED DESCRIPTION OF THE INVENTION

Referring to FIG. 1, a pulse controlled phase modulator 1 receives a continuous wave (CW) coherent input signal 2 and a pulsed input signal 3 and produces a continuous wave phase modulated output signal 4. As shown in FIG. 2, the output signal 4, resulting from the pulsed input signal 3, such as a signal A, is a constant magnitude binary phase shift keying (BPSK) signal, such as a signal B, with the same frequency as the CW input signal 2. For example, using the CW input signal 2 as $I\sin(x + 0^\circ)$, when the pulsed input signal 3 is ON, the output signal is $I\sin(x + 0^\circ)$, and when the pulsed input signal 3 is OFF, the output signal 4 is an inverted signal of $I\sin(x + 180^\circ)$ which is equal to $-I\sin(x + 0^\circ)$.

As shown in FIG. 3, the pulse controlled phase modulator 1 consists of a splitter 5, an independent stage 6, a dependent stage 7, and a combiner 8. The splitter 5 receives the continuous wave input signal 2 and divides it into two signals: an independent signal 9 and a dependent signal 10. Connected to the splitter 5 are the independent stage 6 and the dependent stage 7. The independent stage 6 produces a processed independent signal 11. In the independent stage 6, the independent signal 9 is maintained as a comparison to the dependent signal 10 and is used to produce the phase modulated output signal 4 that is a continuous wave signal.

The dependent stage 7 is used to convert the switching mechanism from the unknown phase pulsed input signal 3 to a pulsed processed dependent signal 12 with a phase opposite to and a magnitude preferably twice that of the processed independent signal 11.

The dependent stage 7 has two sections: an amplifying section 13 and a switching section 14. The amplifying section 13 increases the magnitude of the dependent signal 10 so that it is preferably twice the magnitude of the processed independent signal 11 and the switching section 14 converts the dependent signal 10 from a continuous wave signal to a pulsed signal.

The processed independent signal 11 and the processed dependent signal 12 are then directed into the combiner 8 which combines them to produce the continuous wave phase modulated output signal 4.

The following description illustrates the pulse controlled phase modulator 1 operation and implementation by way of example only.

The CW input signal 2 is an externally generated continuous wave coherent signal with a preferably fixed frequency, phase, and magnitude. The CW input signal 2 is preferably a laser beam. For example, the CW input signal 2 can be expressed as

$$\text{Input} = 2I\sin(x + 0^\circ)$$

where I is a relative measure of magnitude.

Referring to FIG. 3, the CW input signal 2 is directed into the input of the splitter 5. The splitter 5 can be any suitable splitter known in the art, such as an integrated optic Y-branch or directional coupler. The splitter 5 receives the CW input signal 2 and divides it into two preferably equal signals: the independent signal 9 and the dependent signal 10. For example, the splitter 5, receiving the CW input signal 2 above, will produce the independent signal 9 and the dependent signal 10 of

$$\text{Independent} = I \sin(x + 0^\circ)$$

$$\text{Dependent} = I \sin(x + 0^\circ)$$

The independent signal 9 is directed into the independent stage 6 and the dependent signal 10 is directed into the dependent stage 7.

The independent stage 6 consists of a phase inverter 15, such as a half-integral pathlength. The phase inverter 15 receives the independent signal 9 and inverts its phase to produce the processed independent signal 11 so that the processed independent signal 11 is 180° out of phase with (opposite in phase to) the independent signal 9. For example, the phase inverter 15 will produce the processed independent signal 11 of

$$\text{Processed Independent} = I \sin(x + 180^\circ) = -I \sin(x + 0^\circ)$$

The processed independent signal 11 is then directed into the combiner 8.

The dependent stage 7 receives the dependent signal 10 and is composed of the amplifying section 13 and the switching section 14.

The amplifying section 13 receives the dependent signal 10 and consists of an amplifier 16, such as a semiconductor laser amplifier or an erbium-doped waveguide. The amplifier 16 receives the dependent signal 10 and increases its magnitude to produce an amplified signal 17. The amplification of the amplifier 16 is set so that the resulting amplified signal 17 is preferably twice the magnitude of the processed independent signal 11. For example, the amplifier 16 with an amplification factor of 2 will produce the amplified signal 17 of

$$\text{Amplified} = 2I \sin(x + 0^\circ)$$

The switching section 14 receives the amplified signal 17 and consists of a transmitting switch 18, preferably a saturable absorber operating near saturation. The transmitting switch 18 receives the amplified signal 17 and the pulsed input signal 3 and produces the processed dependent signal 12. If the pulsed input signal 3 is ON, the transmitting switch 18 transmits partially, or

preferably entirely, the amplified signal 17, which becomes the processed dependent signal 12. For example, if the pulsed input signal 3 is ON, the processed dependent signal 12 is

$$\text{Processed Dependent} = 2I\sin(x + 0^\circ)$$

If the pulsed input signal 3 is OFF, the transmitting switch 18 does not transmit the amplified signal 17 and the processed dependent signal 12 is preferably negligible. For example, if the pulsed input signal 3 is OFF, the processed dependent signal 12 is

$$\text{Processed Dependent} = 0$$

The processed dependent signal 12 is then directed into the combiner 8. The combiner 8 can be any suitable combiner known in the art, such as an integrated optic Y-branch or directional coupler. The combiner 8 combines the processed independent signal 11 and the processed dependent signal 12 to produce the output signal 4. For example, the combiner 8 produces two possible output signals 4,

$$\text{Output} = I\sin(x + 0^\circ)$$

if the pulsed input signal 3 is ON, and

$$\text{Output} = I\sin(x + 180^\circ) = -I\sin(x + 0^\circ)$$

if the pulsed input signal 3 is OFF. The output signal 4 is a continuous wave signal with constant magnitude and one of two relative phase values that are opposite in phase.

Preferably, none of the components modify the frequency or polarization of the signals as they propagate through the pulse controlled phase modulator device 1.

Table 1 summarizes the magnitudes and phases of the signals in the pulse controlled phase modulator 1 for the two cases when the pulsed input signal 3 is ON and when the pulsed input signal 3 is OFF.

Table 1

Signal	Pulsed Input Signal 3	CW Input Signal 2	Independent Signal 9	Dependent Signal 10	Amplified Signal 17	Processed Dependent Signal 12	Processed Independent Signal 11	Output Signal 4
Value	ON	2	1	1	2	2	-1	1
Value	OFF	2	1	1	2	0	-1	-1

The processed dependent signal 12 does not have to be twice the magnitude of the processed independent signal 11. However, the processed dependent signal 12 and the processed independent signal 11 should combine to produce two possible output signal 4 values of equal magnitude and opposite phase.

An alternative embodiment of the pulse controlled phase modulator 1 is shown in FIG. 4 where like numerals with a prefix 10 refer to similar elements of the pulse controlled phase modulator 1 in FIG. 3. The order of an amplifying section 1013 and a switching section 1014, in a dependent stage 107 of a pulse controlled phase modulator 101, is reversed so that the amplifying section 1013 follows the switching section 1014. Also, the amplifying section 1013 is subdivided into a boosting segment 19 and a filtering segment 20. The boosting segment 19 is used to increase the magnitude of a switched signal 21, producing a boosted signal 22. The filtering segment 20 is used to make the resulting boosted signal 22, which becomes a processed dependent signal 1012, either a negligible signal or the processed dependent signal 1012 with a magnitude preferably twice that of a processed independent signal 1011. The filtering segment 20 is useful for suppressing unwanted boosted signals 22, such as spontaneous emission signals in a semiconductor laser amplifier. A threshold device 23, such as a saturable absorber, is used in the filtering segment 20.

A CW input signal 102 is directed into the input of a splitter 105 which divides the CW input signal 102 into two preferably equal signals: an independent signal 109 and a dependent signal 1010. The independent signal 109 is directed into an independent stage 106 and the dependent signal 1010 is directed into the dependent stage 107.

The independent stage 106 receives the independent signal 109 and consists of a phase inverter 1015. The phase inverter 1015 receives the independent signal 109 and inverts its phase to produce the processed independent signal 1011, so that the processed independent signal 1011 is opposite in phase to the independent signal 109. The processed independent signal 1011 is then directed into a combiner 108.

The dependent stage 107 receives the dependent signal 1010 and is composed of the switching section 1014 and the amplifying section 1013.

The switching section 1014 receives the dependent signal 1010 and consists of a transmitting switch 1018, preferably a threshold device operating near its threshold, such as a saturable absorber operating near saturation. The transmitting switch 1018 receives the dependent signal 1010 and a pulsed input signal 103 and produces the switched signal 21. If the pulsed input signal 103 is ON, the transmitting switch 1018 transmits partially, or preferably entirely, the dependent signal 1010, which becomes the switched signal 21. If the pulsed input signal 103 is OFF, the transmitting switch 1018 does not transmit the dependent signal 1010 and the switched signal 21 is preferably negligible.

The amplifying section 1013 receives the switched signal 21 and is composed of the boosting segment 19 and the filtering segment 20. The boosting segment 19 consists of an amplifier 1016 and receives the switched signal 21. The amplifier 1016 increases the magnitude of the switched signal

21 to produce the boosted signal 22. The amplification of the amplifier 1016 is set so that the resulting dependent signal 1012 is preferably twice the magnitude of the processed independent signal 1011.

The filtering segment 20 receives the boosted signal 22 and transmits the boosted signal 22 when it is larger in magnitude than, or equal in magnitude to, a threshold value, such as when the pulsed input signal 103 is ON. The filtering segment 20 does not transmit the boosted signal 22 when it is smaller in magnitude than the threshold value, such as when the pulsed input signal 103 is OFF and a small spontaneous noise signal is generated by a semiconductor laser amplifier in the boosting segment 19. The filtering segment 20 consists of a threshold device 23, such as a saturable absorber. The threshold device 23 receives the boosted signal 22 and produces the processed dependent signal 1012. If the magnitude of the boosted signal 22 is less than the threshold value of the threshold device 23, the boosted signal 22 is not transmitted and the processed dependent signal 1012 is negligible. If the magnitude of the boosted signal 22 is greater than, or equal to, the threshold value of the threshold device 23, the boosted signal 22 is transmitted partially, or preferably entirely, and becomes the processed dependent signal 1012. The processed dependent signal 1012 is then directed into the combiner 108.

The combiner 108 receives the processed independent signal 1011 and the processed dependent signal 1012 and combines them to produce an output signal 104. The output signal 104 is a continuous wave signal with constant magnitude and one of two relative phase values that are opposite in phase.

Preferably, none of the components modify the frequency or polarization of the signals as they propagate through the pulse controlled phase modulator device 101.

Table 2 summarizes the magnitudes and phases of example signals in the pulse controlled phase modulator 101 for the two cases when the pulsed input signal 103 is ON and when the pulsed input signal 103 is OFF.

Table 2

Signal	Pulsed Input Signal 103	CW Input Signal 102	Independent Signal 109	Dependent Signal 1010	Switched Signal 21	Boosted Signal 22	Processed Dependent Signal 1012	Processed Independent Signal 1011	Output Signal 104
Value	ON	2	1	1	1	2	2	-1	1
Value	OFF	2	1	1	0	$\frac{1}{10}$	0	-1	-1

A further alternative embodiment of the pulse controlled phase modulator 1 is shown in FIG. 5, where like numerals with a prefix 20 refer to similar elements of the pulse controlled phase modulators 1, 101 in FIG. 3 and FIG. 4. In a pulse controlled phase modulator 201, a phase inverter 2015 is placed after an amplifier 2016 in an amplifying section 2013 of a dependent stage 207. A phase inverter is not used in an independent stage 206.

A CW input signal 202 is directed into the input of a splitter 205. The splitter 205 receives the CW input signal 202 and divides it into two preferably equal signals: a processed independent signal 2011 and a dependent signal 2010. The processed independent signal 2011 is directed into the independent stage 206 and the dependent signal 2010 is directed into the dependent stage 207.

The independent stage 206 preferably does not alter the processed independent signal 2011 so that it is transmitted through the independent stage 206 and is directed into a combiner 208.

The dependent stage 207 receives the dependent signal 2010 and is composed of the amplifying section 2013 and a switching section 2014.

The amplifying section 2013 receives the dependent signal 2010 and consists of the amplifier 2016 and the phase inverter 2015. The amplifier 2016 receives the dependent signal 2010 and increases the magnitude of the dependent signal 2010 to produce an augmented signal 24. The amplification of the amplifier 2016 is set so that a resulting dependent signal 2012 is preferably twice the magnitude of the processed independent signal 2011.

The augmented signal 24 is then directed into the phase inverter 2015. The phase inverter 2015 inverts the phase of the augmented signal 24 to produce an amplified signal 2017 that is opposite in phase to the augmented signal 24.

The switching section 2014 receives the amplified signal 2017 and consists of a transmitting switch 2018, preferably a threshold device operating near its threshold, such as a saturable absorber operating near saturation. The transmitting switch 2018 receives the amplified signal 2017 and a pulsed input signal 203 and produces the processed dependent signal 2012. If the pulsed input signal 203 is ON, the transmitting switch 2018 transmits partially, or preferably entirely, the amplified signal 2017 which becomes the processed dependent signal 2012. If the pulsed input signal 203 is OFF, the transmitting switch 2018 does not transmit the amplified signal 2017, and the processed dependent signal 2012 is preferably negligible. The processed dependent signal 2012 is then directed into the combiner 208.

The combiner 208 combines the processed independent signal 2011 and the processed dependent signal 2012 to produce an output signal 204. The output signal 204 is a continuous wave signal with constant magnitude and one of two relative phase values that are opposite in phase.

Because the phase inverter 2015 is placed in the dependent stage 207 instead of the independent stage 206, the output signal 204 is inverted with respect to the output signals 4, 104 of the previous embodiments of the pulse controlled phase modulator 1, 101.

Preferably, none of the components modify the frequency or polarization of the signals as they propagate through the pulse controlled phase modulator device 201.

Table 3 summarizes the magnitudes and phases of example signals in the pulse controlled phase modulator 201 for the two cases when the pulsed input signal 203 is ON and when the pulsed input signal 203 is OFF.

Table 3

Signal	Pulsed Input Signal 203	CW Input Signal 202	Processed Independent Signal 2011	Dependent Signal 2010	Augmented Signal 2024	Transmitted Signal 2017	Processed Dependent Signal 2012	Processed Independent Signal 2011	Output Signal 204
Value	ON	2	1	1	2	-2	-2	1	-1
Value	OFF	2	1	1	2	-2	0	1	1

FIG. 6 shows a further alternative embodiment of the pulse controlled phase modulator 1, where like numerals with a prefix 30 refer to similar elements of the pulse controlled phase modulators 1, 101, 201 in FIG. 3, FIG. 4, and FIG. 5. In a pulse controlled phase modulator 301, a first amplifier 25 is placed in an independent stage 306 and the amplification of an amplifying section 3013 in a dependent stage 307 is increased, producing a larger magnitude output signal 304 than the output signals 4, 104, 204 of the previous embodiments of the pulse controlled phase modulator 1, 101, 201.

A CW input signal 302 is directed into the input of a splitter 305. The splitter 305 receives the CW input signal 302 and divides it into two preferably equal signals: an independent signal 309 and a dependent signal 3010. The independent signal 309 is directed into the independent stage 306 and the dependent signal 3010 is directed into the dependent stage 307.

The independent stage 306 consists of a phase inverter 3015 and the first amplifier 25. The phase inverter 3015 receives the independent signal 309 and inverts its phase to produce an inverted independent signal 26 that is opposite in phase to the independent signal 309.

The first amplifier 25 receives the inverted independent signal 26 and increases its magnitude to produce a processed independent signal 3011. The amplification of the first amplifier 25 is set so that the resulting processed independent signal 3011 is preferably half the magnitude of a processed dependent signal 3012. The processed independent signal 3011 is directed into a combiner 308.

The dependent stage 307 receives the dependent signal 3010 and is composed of the amplifying section 3013 and a switching section 3014.

The amplifying section 3013 receives the dependent signal 3010 and consists of a second amplifier 3016. The second amplifier 3016 increases the magnitude of the dependent signal 3010 to produce an amplified signal 3017. The amplification of the second amplifier 3016 is set so that the resulting dependent signal 3012 is preferably twice the magnitude of the processed independent signal 3011.

The switching section 3014 receives the amplified signal 3017 and consists of a transmitting switch 3018, preferably a threshold device operating near its threshold, such as a saturable absorber operating near saturation. The transmitting switch 3018 receives the amplified signal 3017 and a pulsed input signal 303 and produces a processed dependent signal 3012. If the pulsed input signal 303 is ON, the transmitting switch 3018 transmits partially, or preferably entirely, the amplified signal 3017, which becomes the processed dependent signal 3012. If the pulsed input signal 303 is OFF, the transmitting switch 3018 does not transmit the amplified signal 3017 and the processed dependent signal 3012 is preferably negligible. The processed dependent signal 3012 is directed into the combiner 308.

The combiner 308 combines the processed independent signal 3011 and the processed dependent signal 3012 to produce an output signal 304. The output signal 304 is a continuous wave signal with constant magnitude and one of two relative phase values that are opposite in phase.

Preferably, none of the components modify the frequency or polarization of the signals as they propagate through the pulse controlled phase modulator device 301.

Table 4 summarizes the magnitudes and phases of example signals in the pulse controlled phase modulator 301 for the two cases when the pulsed input signal 303 is ON and when the pulsed input signal 303 is OFF.

Table 4

Signal	Pulsed Input Signal 303	CW Input Signal 302	Independent Signal 309	Inverted Independent Signal 26	Dependent Signal 3010	Amplified Signal 3017	Processed Dependent Signal 3012	Processed Independent Signal 3011	Output Signal 304
Value	ON	2	1	-1	1	4	4	-2	2
Value	OFF	2	1	-1	1	4	0	-2	-2

FIG. 7 shows a further alternative embodiment of the pulse controlled phase modulator 1 where like numerals with a prefix 40 refer to similar elements of the pulse controlled phase modulators 1, 101, 201, 301 in FIG. 3, FIG. 4, FIG. 5, and FIG. 6. In a pulse controlled phase

modulator 401, a splitter 405 is weighted so that an independent signal 409 and a dependent signal 4010 are not equal in magnitude and an amplifier in an amplifying section 4013 is not required. An amplifier 4025 is used in an independent stage 406.

A CW input signal 402 is directed into the input of the weighted splitter 405. The weighted splitter 405 receives the CW input signal 402 and divides it into two signals: the independent signal 409 and the dependent signal 4010. For example, the weighted splitter 405 splits in the ratio of 1:4 and from the CW input signal 402

$$\text{Input} = 5I\sin(x + 0^\circ)$$

produces the independent signal 409 and the dependent signal 4010 of

$$\text{Independent} = 1I\sin(x + 0^\circ)$$

$$\text{Dependent} = 4I\sin(x + 0^\circ)$$

The independent signal 409 is directed into the independent stage 406 and the dependent signal 4010 is directed into a dependent stage 407.

The independent stage 406 consists of a phase inverter 4015 and the amplifier 4025. The phase inverter 4015 receives the independent signal 409 and inverts its phase to produce an inverted independent signal 4026 that is opposite in phase to the independent signal 409. For example, the inverted independent signal 4026 is

$$\text{Inverted Independent} = 1I\sin(x + 180^\circ) = -1I\sin(x + 0^\circ)$$

The amplifier 4025 receives the inverted independent signal 4026 and increases the magnitude of the inverted independent signal 4026 to produce a processed independent signal 4011. The amplification of the amplifier 4025 is set so that the resulting processed independent signal 4011 is preferably half the magnitude of a processed dependent signal 4012. For example, the amplifier 4025, with an amplification factor of 2, produces the processed independent signal 4011 of

$$\text{Processed Independent} = -2I\sin(x + 0^\circ)$$

The processed independent signal 4011 is directed into a combiner 408.

The dependent stage 407 receives the dependent signal 4010 and is composed of the amplifying section 4013 and a switching section 4014.

The amplifying section 4013 preferably does not alter the dependent signal 4010 so that it is transmitted through the amplifying section 4013.

The switching section 4014 receives the dependent signal 4010 and consists of a transmitting switch 4018, preferably a threshold device operating near its threshold, such as a saturable absorber operating near saturation. The transmitting switch 4018 receives the dependent signal 4010 and a

pulsed input signal 403 and produces the processed dependent signal 4012. If the pulsed input signal 403 is ON, the transmitting switch 4018 transmits partially, or preferably entirely, the dependent signal 4010, which becomes the processed dependent signal 4012. For example, if the pulsed input signal 403 is ON, the processed dependent signal 4012 is

$$5 \quad \text{Processed Dependent} = 4I\sin(x + 0^\circ)$$

If the pulsed input signal 403 is OFF, the transmitting switch 4018 does not transmit the dependent signal 4010 and the processed dependent signal 4012 is preferably negligible. For example, if the pulsed input signal 403 is OFF, the processed dependent signal 4012 is

$$\text{Processed Dependent} = 0$$

10 The processed dependent signal 4012 is directed into the combiner 408.

The combiner 408 combines the processed independent signal 4011 and the processed dependent signal 4012 to produce an output signal 404. For example, the combiner 408 produces two possible output signals 404,

$$\text{Output} = 2I\sin(x + 0^\circ)$$

15 if the pulsed input signal 403 is ON, and

$$\text{Output} = 2I\sin(x + 180^\circ) = -2I\sin(x + 0^\circ)$$

if the pulsed input signal 403 is OFF. The output signal 404 is a continuous wave signal with constant magnitude and one of two relative phase values that are opposite in phase.

20 Preferably, none of the components modify the frequency or polarization of the signals as they propagate through the pulse controlled phase modulator device 401.

Table 5 summarizes the magnitudes and phases of the example signals in the pulse controlled phase modulator 401 for the two cases when the pulsed input signal 403 is ON and when the pulsed input signal 403 is OFF.

Table 5

Signal	Pulsed Input Signal 403	CW Input Signal 402	Independent Signal 409	Inverted Independent Signal 4026	Dependent Signal 4010	Processed Dependent Signal 4012	Processed Independent Signal 4011	Output Signal 404
Value	ON	5	1	-1	4	4	-2	2
Value	OFF	5	1	-1	4	0	-2	-2

25 The magnitude of the output signal 404 is twice the magnitude of the output signals 4, 104, 204 of the first three embodiments of the pulse controlled phase modulator 1, 101, 201 and can be used with an external unweighted splitter 27 to provide two output signals 28, 29, as shown in Table

6 and FIG. 7, that are equal in magnitude to the output signals 4, 104, 204 of the first three embodiments of the pulse controlled phase modulator 1, 101, 201.

Table 6

Signal	Output Signal 404	First Output Signal 28	Second Output Signal 29
Value	2	1	1
Value	-2	-1	-1

The phase inverter 15 may be placed anywhere in either the dependent stage 7 or the independent stage 6. However, if more than one phase inverter is used, the total number of phase inverters in the pulse controlled phase modulator 1 is preferably odd so that the processed independent signal 11 and the processed dependent signal 12 are opposite in phase.

The pulse controlled phase modulator 1 can be used as a receiver for converting an external pulsed input signal 3, with an unknown phase value, to a binary phase shift keying (BPSK) modulated signal 4 for use in a BPSK circuit. The external pulsed input signal 3 can be a signal from an adjacent circuit or from a fiber optic transmission line. For example, as shown in FIG. 8, four external pulsed input signals 503, with unknown phase values, are received by four pulse controlled phase modulators 1 functioning as receivers 30. The receivers 30 convert the external pulsed input signals 503 to phase modulated signals 504 that are received by a BPSK circuit 31.

An integrated optic embodiment of the pulse controlled phase modulator 1 employs commonly available integrated optic components and operates using laser beams, preferably. A design example pulse controlled phase modulator 601 is shown in FIG. 9 where like numerals with a prefix 60 refer to similar elements of the pulse controlled phase modulator 1 in FIG. 3. The design example pulse controlled phase modulator 601 uses laser light with a wavelength of 0.85 μm . The component dimensions are listed in Table 7.

Table 7

Component	Length
A	157.1 μm
B	42.9 μm
C	100.0 μm
D	16.6 μm
E	100.0 μm
F	49.8 μm
G	123.1 μm
H	26.9 μm
I	18.0 μm
J	314.0 μm
K	18.0 μm

Integrated optic directional couplers 605, 608 are used for the splitter 5 and the combiner 8. Interconnecting waveguides 602, 6010, 6017, 603, 6012, 604, 606 are used to direct signals from component to component. The directional couplers 605, 608 and the waveguides 602, 6010, 6017, 603, 6012, 604, 606 are composed of $\text{Al}_{0.3}\text{Ga}_{0.7}\text{As}$, have a substrate of $\text{Al}_{0.8}\text{Ga}_{0.2}\text{As}$, and have air above the waveguide. The directional couplers 605, 608 have a waveguide spacing of 1 μm and a coupling coefficient of $0.005 \mu\text{m}^{-1}$. The directional couplers 605, 608 and the waveguides 602, 6010, 6017, 603, 6012, 604, 606 are rib waveguides with a rib width of 1 μm and a rib height of 500 nm where the rib is etched 200 nm. The rib waveguides have an effective index of refraction of 3.247.

A semiconductor laser amplifier 6016 is used for the amplifier 16 and is typically composed of AlGaAs or InGaAsP . The semiconductor laser amplifier 6016 in this design example has an effective index of refraction of 4. The phase inverter 15 is implemented by using a second output port 32 of the first directional coupler 605 which provides an inverted signal. A semiconductor saturable absorber 6018, such as impurity doped GaAs , is used as the transmitting switch 18. The saturable absorber 6018 in this example has an effective index of refraction of 3.5.

The length of the independent stage waveguide 606, from the output of the splitter directional coupler 605 to the input of the combiner directional coupler 608 as indicated by I, J, and K, is an integral number of wavelengths since the splitter directional coupler 605 provides an independent signal that is inverted. The number of wavelengths is

$$\frac{3.247}{0.85 \mu\text{m}} (18.0 \mu\text{m} + 314.0 \mu\text{m} + 18.0 \mu\text{m}) = 1337 \text{ wavelengths}$$

where 3.247 is the effective refractive index of the independent stage waveguide 606 and $0.85\text{ }\mu\text{m}$ is the wavelength of light used. Reflecting mirrors 33 are used to direct the beams in the independent stage waveguide 606.

- 5 Although the invention has been described with reference to certain specific embodiments, various modifications thereof will be apparent to those skilled in the art without departing from the spirit and scope of the invention as outlined in the claims appended hereto.

CLAIMS

I claim:

1. A pulse controlled phase modulator device comprising:
 - a) a continuous wave coherent input signal;
 - b) a pulsed input signal;
 - c) a splitter for receiving said continuous wave coherent input signal, said splitter dividing said continuous wave coherent input signal to produce an independent signal and a dependent signal;
 - d) an independent stage for receiving said independent signal, said independent stage producing a processed independent signal that is not pulse modulated;
 - e) a dependent stage for receiving said pulsed input signal and said dependent signal, said dependent stage pulse modulating said dependent signal to produce a processed dependent signal; and
 - f) a combiner for receiving said processed independent signal and said processed dependent signal, said combiner combining said processed independent signal and said processed dependent signal to produce a continuous wave coherent phase modulated output signal.
2. A device according to claim 1 having an ON operating region and an OFF operating region.
3. A device according to claim 2, where in said ON operating region said processed dependent signal is substantially non-negligible and substantially opposite in phase to said processed independent signal and said pulsed input signal is present.
4. A device according to claim 2, where in said OFF operating region said processed dependent signal is substantially negligible in magnitude and said pulsed input signal is not present.
5. A device according to claim 2, where in said ON operating region said output signal is substantially equal in magnitude and substantially opposite in phase to said output signal in said OFF operating region.
6. A device according to claim 1, wherein said signals are laser beams.
7. A device according to claim 1, wherein said independent stage includes at least one amplifier for increasing the magnitude of said independent signal by a predetermined factor.
8. A device according to claim 7, wherein said amplifier is a semiconductor laser amplifier.

9. A device according to claim 1, wherein said independent stage includes at least one phase inverter for making said processed independent signal substantially opposite in phase to said processed dependent signal.

10. A device according to claim 1, wherein said dependent stage comprises:

- a) an amplifying section for receiving said dependent signal, said amplifying section producing a boosted signal; and
- b) a switching section that receives said boosted signal and said pulsed input signal, said switching section pulse modulating said boosted signal to produce said processed dependent signal that is

substantially non-negligible and substantially opposite in phase to said processed independent signal in said ON operating region and is substantially negligible in said OFF operating region.

11. A device according to claim 10, wherein said amplifying section includes at least one amplifier for increasing the magnitude of said dependent signal by a predetermined factor.

12. A device according to claim 11, wherein said at least one amplifier is a semiconductor laser amplifier.

13. A device according to claim 10, wherein said amplifying section includes at least one phase inverter for making said processed dependent signal substantially opposite in phase to said processed independent signal.

14. A device according to claim 10, wherein said switching section includes a transmitting switch.

15. A device according to claim 14, wherein said transmitting switch transmits said boosted signal when said pulsed input signal is present and does not transmit said boosted signal when said pulsed input signal is not present.

16. A device according to claim 14, wherein said transmitting switch partially transmits said boosted signal when said pulsed input signal is present and does not transmit said boosted signal when said pulsed input signal is not present.

17. A device according to claim 14, wherein said transmitting switch is a saturable absorber.

18. A device according to claim 10, wherein said switching section includes at least one phase inverter for making said processed dependent signal substantially opposite in phase to said processed independent signal.

19. A device according to claim 1, wherein said dependent stage comprises:

- a) a switching section that receives said dependent signal and said pulsed input signal, said switching section pulse modulating said dependent signal to produce a switched signal; and
- b) an amplifying section for receiving said switched signal, said amplifying section producing said processed dependent signal that is substantially non-negligible and substantially opposite in phase to said processed independent signal in said ON operating region and is substantially negligible in said OFF operating region.

20. A device according to claim 19, wherein said switching section includes a transmitting switch.

21. A device according to claim 20, wherein said transmitting switch transmits said dependent signal when said pulsed input signal is present and does not transmit said dependent signal when said pulsed input signal is not present.

22. A device according to claim 20, wherein said transmitting switch partially transmits said dependent signal when said pulsed input signal is present and does not transmit said dependent signal when said pulsed input signal is not present.

23. A device according to claim 20, wherein said transmitting switch is a saturable absorber.

24. A device according to claim 19, wherein said switching section includes at least one phase inverter for making said processed dependent signal substantially opposite in phase to said processed independent signal.

25. A device according to claim 19, wherein said amplifying section comprises:

- a) a boosting segment for receiving said switched signal, said boosting segment providing a boosted signal; and
- b) a filtering segment for receiving said boosted signal, said filtering segment providing said processed dependent signal that is substantially non-negligible and substantially opposite in phase to said processed independent signal in said ON operating region and is substantially negligible in said OFF operating region.

26. A device according to claim 25, wherein said boosting segment includes at least one amplifier for increasing the magnitude of said switched signal by a predetermined factor.

27. A device according to claim 26, wherein said at least one amplifier is a semiconductor laser amplifier.

28. A device according to claim 25, wherein said boosting segment includes at least one phase inverter for making said processed dependent signal substantially opposite in phase to said processed independent signal.
29. A device according to claim 25, wherein said filtering segment includes a threshold device.
30. A device according to claim 29, wherein said threshold device transmits said boosted signal in said ON operating region when the magnitude of said boosted signal is greater than a predetermined threshold magnitude and when the magnitude of said boosted signal is equal to said predetermined threshold magnitude and does not transmit said boosted signal in said OFF operating region when the magnitude of said boosted signal is less than said predetermined threshold magnitude.
31. A device according to claim 29, wherein said threshold device partially transmits said boosted signal in said ON operating region when the magnitude of said boosted signal is greater than a predetermined threshold magnitude and when the magnitude of said boosted signal is equal to said predetermined threshold magnitude and does not transmit said boosted signal in said OFF operating region when the magnitude of said boosted signal is less than said predetermined threshold magnitude.
32. A device according to claim 29, wherein said threshold device is a saturable absorber.
33. A device according to claim 25, wherein said filtering segment includes at least one phase inverter for making said processed dependent signal substantially opposite in phase to said processed independent signal.

ABSTRACT OF THE DISCLOSURE

A pulse controlled phase modulator device converts an unknown phase pulsed input signal to a continuous wave phase modulated output signal. The pulsed input signal activates a switch, such as a saturable absorber operating near saturation, to pulse modulate a dependent signal that has a known phase value. A combiner combines the dependent signal with an independent signal to produce the constant magnitude continuous wave phase modulated output signal. The output signal is a binary phase shift keying signal with the same frequency as the continuous wave input signal. An amplifier or weighted splitter is used to make the dependent signal larger in magnitude than the independent signal and a phase inverter is used to make the dependent and independent signals opposite in phase.

The pulse controlled phase modulator consists of a splitter, an independent stage, a dependent stage, and a combiner. A threshold device is also used on the pulsed dependent signal to inhibit output magnitude variations.




FIG. 1




FIG. 2

+

2/8




FIG. 3

+

+

3/8





FIG. 4

+



+

5/8




FIG. 6

+

+

6/8




FIG. 7

+

+

FIG. 8 is a schematic diagram of a system 30, 31, 503, 504, 505, 506, 507, 508, 509, 510, 511, 512, 513, 514, 515, 516, 517, 518, 519, 520, 521, 522, 523, 524, 525, 526, 527, 528, 529, 530, 531, 532, 533, 534, 535, 536, 537, 538, 539, 540, 541, 542, 543, 544, 545, 546, 547, 548, 549, 550, 551, 552, 553, 554, 555, 556, 557, 558, 559, 560, 561, 562, 563, 564, 565, 566, 567, 568, 569, 570, 571, 572, 573, 574, 575, 576, 577, 578, 579, 580, 581, 582, 583, 584, 585, 586, 587, 588, 589, 590, 591, 592, 593, 594, 595, 596, 597, 598, 599, 600, 601, 602, 603, 604, 605, 606, 607, 608, 609, 610, 611, 612, 613, 614, 615, 616, 617, 618, 619, 620, 621, 622, 623, 624, 625, 626, 627, 628, 629, 630, 631, 632, 633, 634, 635, 636, 637, 638, 639, 640, 641, 642, 643, 644, 645, 646, 647, 648, 649, 650, 651, 652, 653, 654, 655, 656, 657, 658, 659, 660, 661, 662, 663, 664, 665, 666, 667, 668, 669, 670, 671, 672, 673, 674, 675, 676, 677, 678, 679, 680, 681, 682, 683, 684, 685, 686, 687, 688, 689, 690, 691, 692, 693, 694, 695, 696, 697, 698, 699, 700, 701, 702, 703, 704, 705, 706, 707, 708, 709, 710, 711, 712, 713, 714, 715, 716, 717, 718, 719, 720, 721, 722, 723, 724, 725, 726, 727, 728, 729, 730, 731, 732, 733, 734, 735, 736, 737, 738, 739, 740, 741, 742, 743, 744, 745, 746, 747, 748, 749, 750, 751, 752, 753, 754, 755, 756, 757, 758, 759, 760, 761, 762, 763, 764, 765, 766, 767, 768, 769, 770, 771, 772, 773, 774, 775, 776, 777, 778, 779, 780, 781, 782, 783, 784, 785, 786, 787, 788, 789, 790, 791, 792, 793, 794, 795, 796, 797, 798, 799, 800, 801, 802, 803, 804, 805, 806, 807, 808, 809, 810, 811, 812, 813, 814, 815, 816, 817, 818, 819, 820, 821, 822, 823, 824, 825, 826, 827, 828, 829, 830, 831, 832, 833, 834, 835, 836, 837, 838, 839, 840, 841, 842, 843, 844, 845, 846, 847, 848, 849, 850, 851, 852, 853, 854, 855, 856, 857, 858, 859, 860, 861, 862, 863, 864, 865, 866, 867, 868, 869, 870, 871, 872, 873, 874, 875, 876, 877, 878, 879, 880, 881, 882, 883, 884, 885, 886, 887, 888, 889, 890, 891, 892, 893, 894, 895, 896, 897, 898, 899, 900, 901, 902, 903, 904, 905, 906, 907, 908, 909, 910, 911, 912, 913, 914, 915, 916, 917, 918, 919, 920, 921, 922, 923, 924, 925, 926, 927, 928, 929, 930, 931, 932, 933, 934, 935, 936, 937, 938, 939, 940, 941, 942, 943, 944, 945, 946, 947, 948, 949, 950, 951, 952, 953, 954, 955, 956, 957, 958, 959, 960, 961, 962, 963, 964, 965, 966, 967, 968, 969, 970, 971, 972, 973, 974, 975, 976, 977, 978, 979, 980, 981, 982, 983, 984, 985, 986, 987, 988, 989, 990, 991, 992, 993, 994, 995, 996, 997, 998, 999, 1000.

7/8




FIG. 8

+

+




FIG. 9

+

Please type a plus sign (+) inside this box → ☐

PTO/SB/01 (12-97)
Approved for use through 9/30/00. OMB 0651-0032
Patent and Trademark Office; U.S. DEPARTMENT OF COMMERCE

Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it contains a valid OMB control number.

DECLARATION FOR UTILITY OR DESIGN PATENT APPLICATION (37 CFR 1.63) <input checked="" type="checkbox"/> Declaration Submitted with Initial Filing OR <input type="checkbox"/> Declaration Submitted after Initial Filing (surcharge (37 CFR 1.16 (e)) required)	Attorney Docket Number	2000-003
	First Named Inventor	Charles C. Romaniuk
	COMPLETE IF KNOWN	
	Application Number	/
	Filing Date	
	Group Art Unit	
	Examiner Name	

As a below named inventor, I hereby declare that:

My residence, post office address, and citizenship are as stated below next to my name.

I believe I am the original, first and sole inventor (if only one name is listed below) or an original, first and joint inventor (if plural names are listed below) of the subject matter which is claimed and for which a patent is sought on the invention entitled:

Pulse Controlled Phase Modulator

the specification of which (Title of the Invention)

☒ is attached hereto
OR
☐ was filed on (MM/DD/YYYY) as United States Application Number or PCT International Application Number and was amended on (MM/DD/YYYY) (if applicable).

I hereby state that I have reviewed and understand the contents of the above identified specification, including the claims, as amended by any amendment specifically referred to above.

I acknowledge the duty to disclose information which is material to patentability as defined in 37 CFR 1.56.

I hereby claim foreign priority benefits under 35 U.S.C. 119(a)-(d) or 365(b) of any foreign application(s) for patent or inventor's certificate, or 365(a) of any PCT international application which designated at least one country other than the United States of America, listed below and have also identified below, by checking the box, any foreign application for patent or inventor's certificate, or of any PCT international application having a filing date before that of the application on which priority is claimed.

Prior Foreign Application Number(s)	Country	Foreign Filing Date (MM/DD/YYYY)	Priority Not Claimed	Certified Copy Attached?	
				YES	NO
			<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
			<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
			<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>
			<input type="checkbox"/>	<input type="checkbox"/>	<input type="checkbox"/>

☐ Additional foreign application numbers are listed on a supplemental priority data sheet PTO/SB/02B attached hereto:

I hereby claim the benefit under 35 U.S.C. 119(e) of any United States provisional application(s) listed below.

Application Number(s)	Filing Date (MM/DD/YYYY)

☐ Additional provisional application numbers are listed on a supplemental priority data sheet PTO/SB/02B attached hereto.

[Page 1 of 2]

Burden Hour Statement: This form is estimated to take 0.4 hours to complete. Time will vary depending upon the needs of the individual case. Any comments on the amount of time you are required to complete this form should be sent to the Chief Information Officer, Patent and Trademark Office, Washington, DC 20231. DO NOT SEND FEES OR COMPLETED FORMS TO THIS ADDRESS. SEND TO: Assistant Commissioner for Patents, Washington, DC 20231.

Please type a plus sign (+) inside this box →



PTO/SB/01 (12-97)
Approved for use through 9/30/00. OMB 0651-0032
Patent and Trademark Office; U.S. DEPARTMENT OF COMMERCE

Under the Paperwork Reduction Act of 1995, no persons are required to respond to a collection of information unless it contains a valid OMB control number.

DECLARATION — Utility or Design Patent Application

I hereby claim the benefit under 35 U.S.C. 120 of any United States application(s), or 365(c) of any PCT international application designating the United States of America, listed below and, insofar as the subject matter of each of the claims of this application is not disclosed in the prior United States or PCT International application in the manner provided by the first paragraph of 35 U.S.C. 112, I acknowledge the duty to disclose information which is material to patentability as defined in 37 CFR 1.56 which became available between the filing date of the prior application and the national or PCT international filing date of this application.

U.S. Parent Application or PCT Parent Number	Parent Filing Date (MM/DD/YYYY)	Parent Patent Number (if applicable)

☐ Additional U.S. or PCT international application numbers are listed on a supplemental priority data sheet PTO/SB/02B attached hereto.

As a named inventor, I hereby appoint the following registered practitioner(s) to prosecute this application and to transact all business in the Patent and Trademark Office connected therewith:

☐ Customer Number

OR

☐ Registered practitioner(s) name/registration number listed below

Place Customer
Number Bar Code
Label here

Name	Registration Number	Name	Registration Number

☐ Additional registered practitioner(s) named on supplemental Registered Practitioner Information sheet PTO/SB/02C attached hereto.

Direct all correspondence to: ☐ Customer Number or Bar Code Label ☐ OR ☒ Correspondence address below

Name	Charles C. Romaniuk				
Address	Box 3295				
Address					
City	Vermilion	State	Alberta	ZIP	T9X 2B2
Country	Canada	Telephone	(403) 861-6944	Fax	

I hereby declare that all statements made herein of my own knowledge are true and that all statements made on information and belief are believed to be true; and further that these statements were made with the knowledge that willful false statements and the like so made are punishable by fine or imprisonment, or both, under 18 U.S.C. 1001 and that such willful false statements may jeopardize the validity of the application or any patent issued thereon.

Name of Sole or First Inventor:

☐ A petition has been filed for this unsigned inventor

Given Name (first and middle (if any))	Family Name or Surname
Charles Christopher	Romaniuk

Inventor's Signature	<i>Charles Romaniuk</i>			Date	09/20/00
Residence: City	Calgary	State	Alberta	Country	Canada
Post Office Address	Box 3295				
Post Office Address					
City	Vermilion	State	Alberta	ZIP	T9X 2B2
Country	Canada				

☐ Additional inventors are being named on the _____ supplemental Additional Inventor(s) sheet(s) PTO/SB/02A attached hereto